



## OVERHEAD TEMPORARY

1. A temporary service should be secured to a pole or other convenient place as approved by the Electrical Inspector. No services allowed on tree or other vegetation.
2. A 120-Volt receptacle is required it must be GFCI protected with a weatherproof enclosure. In use type. Extra Duty is only type approved.
3. 30 AMP 125 Volt Travel Trailer receptacle and or 50-amp 4 wire RV receptacle may be installed and are not required to be GFCI protected. All other receptacles installed outdoors are required to be GFCI protected.
4. A temporary shall have a 2(two)-year time limit. After that, a new permit must be purchased, and an inspection called for.
5. A temporary service is not meant to be a final. If more time is needed for the construction project, "special permission" must be obtained from the inspector.
6. Required 25ft pole, minimum 4' 6" in the ground.
7. All wiring must meet the current National Electric Code.

Approved by Inspector: 06/13/2014

Last Updated: 8/5/2021

K:\Front Office\Templates\Overhead Temporary.pdf (CSR)

K:\Administrative\BCES Service Policies\Customer Reference Sheets\Overhead Temporary.ppt (Editable)